FORMALIZED MATHEMATICS
Volume 11, Number 1, 2003
University of Białystok

Trigonometric Functions on Complex Space

Takashi Mitsuishi
Miyagi University

Noboru Endou
Gifu National College of Technology

Keiji Ohkubo
Shinshu University
Nagano

Summary. This article describes definitions of sine, cosine, hyperbolic sine and hyperbolic cosine. Some of their basic properties are discussed.

MML Identifier: SIN_COS3.

The notation and terminology used here are introduced in the following papers: [9], [4], [10], [1], [8], [2], [3], [5], [7], [11], and [6].

1. Definitions of Trigonometric Functions

We adopt the following convention: x, y denote elements of $\mathbb{R}$, z, z_1, z_2 denote elements of $\mathbb{C}$, and n denotes a natural number.

The function $\sin_{\mathbb{C}}$ from $\mathbb{C}$ into $\mathbb{C}$ is defined by:

(Def. 1) $\sin_{\mathbb{C}}(z) = \frac{\exp(i\cdot z)-\exp(-i\cdot z)}{(2+0i)\cdot i}$.

The function $\cos_{\mathbb{C}}$ from $\mathbb{C}$ into $\mathbb{C}$ is defined by:

(Def. 2) $\cos_{\mathbb{C}}(z) = \frac{\exp(i\cdot z)+\exp(-i\cdot z)}{2+0i}$.

The function $\sinh_{\mathbb{C}}$ from $\mathbb{C}$ into $\mathbb{C}$ is defined by:

(Def. 3) $\sinh_{\mathbb{C}}(z) = \frac{\exp z-\exp(-z)}{2+0i}$.

The function $\cosh_{\mathbb{C}}$ from $\mathbb{C}$ into $\mathbb{C}$ is defined by:

(Def. 4) $\cosh_{\mathbb{C}}(z) = \frac{\exp z+\exp(-z)}{2+0i}$.

© 2003 University of Białystok
ISSN 1426–2630

2. Properties of Trigonometric Functions on Complex Space

We now state a number of propositions:

(1) For every element z of $\mathbb{C}$ holds $\sin_{\mathbb{C}} z \cdot \sin_{\mathbb{C}} z + \cos_{\mathbb{C}} z \cdot \cos_{\mathbb{C}} z = 1_{\mathbb{C}}$.

(2) $-\sin_{\mathbb{C}} z = \sin_{\mathbb{C}} -z$.

(3) $\cos_{\mathbb{C}} z = \cos_{\mathbb{C}} -z$.

(4) $\sin_{\mathbb{C}} z_1 + z_2 = \sin_{\mathbb{C}} z_1 \cdot \cos_{\mathbb{C}} z_2 + \cos_{\mathbb{C}} z_1 \cdot \sin_{\mathbb{C}} z_2$.

(5) $\sin_{\mathbb{C}} z_1 - z_2 = \sin_{\mathbb{C}} z_1 \cdot \cos_{\mathbb{C}} z_2 - \cos_{\mathbb{C}} z_1 \cdot \sin_{\mathbb{C}} z_2$.

(6) $\cos_{\mathbb{C}} z_1 + z_2 = \cos_{\mathbb{C}} z_1 \cdot \cos_{\mathbb{C}} z_2 - \sin_{\mathbb{C}} z_1 \cdot \sin_{\mathbb{C}} z_2$.

(7) $\cos_{\mathbb{C}} z_1 - z_2 = \cos_{\mathbb{C}} z_1 \cdot \cos_{\mathbb{C}} z_2 + \sin_{\mathbb{C}} z_1 \cdot \sin_{\mathbb{C}} z_2$.

(8) $\cosh_{\mathbb{C}} z \cdot \cosh_{\mathbb{C}} z - \sinh_{\mathbb{C}} z \cdot \sinh_{\mathbb{C}} z = 1_{\mathbb{C}}$.

(9) $-\sinh_{\mathbb{C}} z = \sinh_{\mathbb{C}} -z$.

(10) $\cosh_{\mathbb{C}} z = \cosh_{\mathbb{C}} -z$.

(11) $\sinh_{\mathbb{C}} z_1 + z_2 = \sinh_{\mathbb{C}} z_1 \cdot \cosh_{\mathbb{C}} z_2 + \cosh_{\mathbb{C}} z_1 \cdot \sinh_{\mathbb{C}} z_2$.

(12) $\sinh_{\mathbb{C}} z_1 - z_2 = \sinh_{\mathbb{C}} z_1 \cdot \cosh_{\mathbb{C}} z_2 - \cosh_{\mathbb{C}} z_1 \cdot \sinh_{\mathbb{C}} z_2$.

(13) $\cosh_{\mathbb{C}} z_1 - z_2 = \cosh_{\mathbb{C}} z_1 \cdot \cosh_{\mathbb{C}} z_2 - \sinh_{\mathbb{C}} z_1 \cdot \sinh_{\mathbb{C}} z_2$.

(14) $\cosh_{\mathbb{C}} z_1 + z_2 = \cosh_{\mathbb{C}} z_1 \cdot \cosh_{\mathbb{C}} z_2 + \sinh_{\mathbb{C}} z_1 \cdot \sinh_{\mathbb{C}} z_2$.

(15) $\sin_{\mathbb{C}} i \cdot z = i \cdot \sinh_{\mathbb{C}} z$.

(16) $\cos_{\mathbb{C}} i \cdot z = \cosh_{\mathbb{C}} z$.

(17) $\sinh_{\mathbb{C}} i \cdot z = i \cdot \sin_{\mathbb{C}} z$.

(18) $\cosh_{\mathbb{C}} i \cdot z = \cos_{\mathbb{C}} z$.

(19) For all elements x, y of $\mathbb{R}$ holds $\exp(x + yi) = \exp(x) \cdot \cos(y) + (\exp(x) \cdot \sin(y))i$.

(20) $\exp(0_{\mathbb{C}}) = 1 + 0i$.

(21) $\sin_{\mathbb{C}} 0_{\mathbb{C}} = 0_{\mathbb{C}}$.

(22) $\sinh_{\mathbb{C}} 0_{\mathbb{C}} = 0_{\mathbb{C}}$.

(23) $\cos_{\mathbb{C}} 0_{\mathbb{C}} = 1 + 0i$.

(24) $\cosh_{\mathbb{C}} 0_{\mathbb{C}} = 1 + 0i$.

(25) $\exp z = \cosh_{\mathbb{C}} z + \sinh_{\mathbb{C}} z$.

(26) $\exp(-z) = \cosh_{\mathbb{C}} z - \sinh_{\mathbb{C}} z$.

(27) $\exp(z + (2 \cdot \pi + 0i) \cdot i) = \exp z$ and $\exp(z + (0 + (2 \cdot \pi)i)) = \exp z$.

(28) $\exp(0 + (2 \cdot \pi \cdot n)i) = 1 + 0i$ and $\exp((2 \cdot \pi \cdot n + 0i) \cdot i) = 1 + 0i$.

(29) $\exp(0 + (-2 \cdot \pi \cdot n)i) = 1 + 0i$ and $\exp((-2 \cdot \pi \cdot n + 0i) \cdot i) = 1 + 0i$.

(30) $\exp(0 + ((2 \cdot n + 1) \cdot \pi)i) = -1 + 0i$ and $\exp(((2 \cdot n + 1) \cdot \pi + 0i) \cdot i) = -1 + 0i$.

(31) $\exp(0 + (-(2 \cdot n + 1) \cdot \pi)i) = -1 + 0i$ and $\exp((-(2 \cdot n + 1) \cdot \pi + 0i) \cdot i) = -1 + 0i$.

(32) $\exp(0 + ((2 \cdot n + \frac{1}{2}) \cdot \pi)i) = 0 + 1i$ and $\exp(((2 \cdot n + \frac{1}{2}) \cdot \pi + 0i) \cdot i) = 0 + 1i$.

(33) $\exp(0+(-(2\cdot n+\frac{1}{2})\cdot\pi)i) = 0+(-1)i$ and $\exp((-(2\cdot n+\frac{1}{2})\cdot\pi+0i)\cdot i) = 0+(-1)i$.

(34) $\sin_{\mathbb{C}}{}_{z+(2\cdot n\cdot\pi+0i)} = \sin_{\mathbb{C}}{}_{z}$.

(35) $\cos_{\mathbb{C}}{}_{z+(2\cdot n\cdot\pi+0i)} = \cos_{\mathbb{C}}{}_{z}$.

(36) $\exp(i\cdot z) = \cos_{\mathbb{C}}{}_{z}+i\cdot\sin_{\mathbb{C}}{}_{z}$.

(37) $\exp(-i\cdot z) = \cos_{\mathbb{C}}{}_{z}-i\cdot\sin_{\mathbb{C}}{}_{z}$.

(38) For every element x of $\mathbb{R}$ holds $\sin_{\mathbb{C}}{}_{x+0i} = \sin(x)+0i$.

(39) For every element x of $\mathbb{R}$ holds $\cos_{\mathbb{C}}{}_{x+0i} = \cos(x)+0i$.

(40) For every element x of $\mathbb{R}$ holds $\sinh_{\mathbb{C}}{}_{x+0i} = \sinh(x)+0i$.

(41) For every element x of $\mathbb{R}$ holds $\cosh_{\mathbb{C}}{}_{x+0i} = \cosh(x)+0i$.

(42) For all elements x, y of $\mathbb{R}$ holds $x+yi = (x+0i)+i\cdot(y+0i)$.

(43) $\sin_{\mathbb{C}}{}_{x+yi} = \sin(x)\cdot\cosh(y)+(\cos(x)\cdot\sinh(y))i$.

(44) $\sin_{\mathbb{C}}{}_{x+(-y)i} = \sin(x)\cdot\cosh(y)+(-\cos(x)\cdot\sinh(y))i$.

(45) $\cos_{\mathbb{C}}{}_{x+yi} = \cos(x)\cdot\cosh(y)+(-\sin(x)\cdot\sinh(y))i$.

(46) $\cos_{\mathbb{C}}{}_{x+(-y)i} = \cos(x)\cdot\cosh(y)+(\sin(x)\cdot\sinh(y))i$.

(47) $\sinh_{\mathbb{C}}{}_{x+yi} = \sinh(x)\cdot\cos(y)+(\cosh(x)\cdot\sin(y))i$.

(48) $\sinh_{\mathbb{C}}{}_{x+(-y)i} = \sinh(x)\cdot\cos(y)+(-\cosh(x)\cdot\sin(y))i$.

(49) $\cosh_{\mathbb{C}}{}_{x+yi} = \cosh(x)\cdot\cos(y)+(\sinh(x)\cdot\sin(y))i$.

(50) $\cosh_{\mathbb{C}}{}_{x+(-y)i} = \cosh(x)\cdot\cos(y)+(-\sinh(x)\cdot\sin(y))i$.

(51) For every natural number n and for every element z of $\mathbb{C}$ holds $(\cos_{\mathbb{C}}{}_{z}+i\cdot\sin_{\mathbb{C}}{}_{z})_{\mathbb{N}}^{n} = \cos_{\mathbb{C}}{}_{(n+0i)\cdot z}+i\cdot\sin_{\mathbb{C}}{}_{(n+0i)\cdot z}$.

(52) For every natural number n and for every element z of $\mathbb{C}$ holds $(\cos_{\mathbb{C}}{}_{z}-i\cdot\sin_{\mathbb{C}}{}_{z})_{\mathbb{N}}^{n} = \cos_{\mathbb{C}}{}_{(n+0i)\cdot z}-i\cdot\sin_{\mathbb{C}}{}_{(n+0i)\cdot z}$.

(53) For every natural number n and for every element z of $\mathbb{C}$ holds $\exp(i\cdot(n+0i)\cdot z) = (\cos_{\mathbb{C}}{}_{z}+i\cdot\sin_{\mathbb{C}}{}_{z})_{\mathbb{N}}^{n}$.

(54) For every natural number n and for every element z of $\mathbb{C}$ holds $\exp(-i\cdot(n+0i)\cdot z) = (\cos_{\mathbb{C}}{}_{z}-i\cdot\sin_{\mathbb{C}}{}_{z})_{\mathbb{N}}^{n}$.

(55) For all elements x, y of $\mathbb{R}$ holds $\frac{1+(-1)i}{2+0i}\cdot\sinh_{\mathbb{C}}{}_{x+yi}+\frac{1+1i}{2+0i}\cdot\sinh_{\mathbb{C}}{}_{x+(-y)i} = (\sinh(x)\cdot\cos(y)+\cosh(x)\cdot\sin(y))+0i$.

(56) For all elements x, y of $\mathbb{R}$ holds $\frac{1+(-1)i}{2+0i}\cdot\cosh_{\mathbb{C}}{}_{x+yi}+\frac{1+1i}{2+0i}\cdot\cosh_{\mathbb{C}}{}_{x+(-y)i} = (\sinh(x)\cdot\sin(y)+\cosh(x)\cdot\cos(y))+0i$.

(57) $\sinh_{\mathbb{C}}{}_{z}\cdot\sinh_{\mathbb{C}}{}_{z} = \frac{\cosh_{\mathbb{C}}{}_{(2+0i)\cdot z}-(1+0i)}{2+0i}$.

(58) $\cosh_{\mathbb{C}}{}_{z}\cdot\cosh_{\mathbb{C}}{}_{z} = \frac{\cosh_{\mathbb{C}}{}_{(2+0i)\cdot z}+(1+0i)}{2+0i}$.

(59) $\sinh_{\mathbb{C}}{}_{(2+0i)\cdot z} = (2+0i)\cdot\sinh_{\mathbb{C}}{}_{z}\cdot\cosh_{\mathbb{C}}{}_{z}$ and $\cosh_{\mathbb{C}}{}_{(2+0i)\cdot z} = (2+0i)\cdot\cosh_{\mathbb{C}}{}_{z}\cdot\cosh_{\mathbb{C}}{}_{z}-(1+0i)$.

(60) $\sinh_{\mathbb{C}}{}_{z_1}\cdot\sinh_{\mathbb{C}}{}_{z_1}-\sinh_{\mathbb{C}}{}_{z_2}\cdot\sinh_{\mathbb{C}}{}_{z_2} = \sinh_{\mathbb{C}}{}_{z_1+z_2}\cdot\sinh_{\mathbb{C}}{}_{z_1-z_2}$ and $\cosh_{\mathbb{C}}{}_{z_1}\cdot\cosh_{\mathbb{C}}{}_{z_1}-\cosh_{\mathbb{C}}{}_{z_2}\cdot\cosh_{\mathbb{C}}{}_{z_2} = \sinh_{\mathbb{C}}{}_{z_1+z_2}\cdot\sinh_{\mathbb{C}}{}_{z_1-z_2}$ and

$\sinh_{\mathbb{C}}(z_1) \cdot \sinh_{\mathbb{C}}(z_1) - \sinh_{\mathbb{C}}(z_2) \cdot \sinh_{\mathbb{C}}(z_2) = \cosh_{\mathbb{C}}(z_1) \cdot \cosh_{\mathbb{C}}(z_1) - \cosh_{\mathbb{C}}(z_2) \cdot \cosh_{\mathbb{C}}(z_2)$.

(61) $\cosh_{\mathbb{C}}(z_1+z_2) \cdot \cosh_{\mathbb{C}}(z_1-z_2) = \sinh_{\mathbb{C}}(z_1) \cdot \sinh_{\mathbb{C}}(z_1) + \cosh_{\mathbb{C}}(z_2) \cdot \cosh_{\mathbb{C}}(z_2)$ and $\cosh_{\mathbb{C}}(z_1+z_2) \cdot \cosh_{\mathbb{C}}(z_1-z_2) = \cosh_{\mathbb{C}}(z_1) \cdot \cosh_{\mathbb{C}}(z_1) + \sinh_{\mathbb{C}}(z_2) \cdot \sinh_{\mathbb{C}}(z_2)$ and $\sinh_{\mathbb{C}}(z_1) \cdot \sinh_{\mathbb{C}}(z_1) + \cosh_{\mathbb{C}}(z_2) \cdot \cosh_{\mathbb{C}}(z_2) = \cosh_{\mathbb{C}}(z_1) \cdot \cosh_{\mathbb{C}}(z_1) + \sinh_{\mathbb{C}}(z_2) \cdot \sinh_{\mathbb{C}}(z_2)$.

(62) $\sinh_{\mathbb{C}}((2+0i) \cdot z_1) + \sinh_{\mathbb{C}}((2+0i) \cdot z_2) = (2 + 0i) \cdot \sinh_{\mathbb{C}}(z_1+z_2) \cdot \cosh_{\mathbb{C}}(z_1-z_2)$ and $\sinh_{\mathbb{C}}((2+0i) \cdot z_1) - \sinh_{\mathbb{C}}((2+0i) \cdot z_2) = (2 + 0i) \cdot \sinh_{\mathbb{C}}(z_1-z_2) \cdot \cosh_{\mathbb{C}}(z_1+z_2)$.

(63) $\cosh_{\mathbb{C}}((2+0i) \cdot z_1) + \cosh_{\mathbb{C}}((2+0i) \cdot z_2) = (2 + 0i) \cdot \cosh_{\mathbb{C}}(z_1+z_2) \cdot \cosh_{\mathbb{C}}(z_1-z_2)$ and $\cosh_{\mathbb{C}}((2+0i) \cdot z_1) - \cosh_{\mathbb{C}}((2+0i) \cdot z_2) = (2 + 0i) \cdot \sinh_{\mathbb{C}}(z_1+z_2) \cdot \sinh_{\mathbb{C}}(z_1-z_2)$.

References

[1] Grzegorz Bancerek. The fundamental properties of natural numbers. *Formalized Mathematics*, 1(**1**):41–46, 1990.
[2] Czesław Byliński. The complex numbers. *Formalized Mathematics*, 1(**3**):507–513, 1990.
[3] Czesław Byliński. Functions from a set to a set. *Formalized Mathematics*, 1(**1**):153–164, 1990.
[4] Krzysztof Hryniewiecki. Basic properties of real numbers. *Formalized Mathematics*, 1(**1**):35–40, 1990.
[5] Jarosław Kotowicz. Real sequences and basic operations on them. *Formalized Mathematics*, 1(**2**):269–272, 1990.
[6] Takashi Mitsuishi and Yuguang Yang. Properties of the trigonometric function. *Formalized Mathematics*, 8(**1**):103–106, 1999.
[7] Yasunari Shidama and Artur Korniłowicz. Convergence and the limit of complex sequences. Series. *Formalized Mathematics*, 6(**3**):403–410, 1997.
[8] Wojciech A. Trybulec. Pigeon hole principle. *Formalized Mathematics*, 1(**3**):575–579, 1990.
[9] Zinaida Trybulec. Properties of subsets. *Formalized Mathematics*, 1(**1**):67–71, 1990.
[10] Edmund Woronowicz. Relations and their basic properties. *Formalized Mathematics*, 1(**1**):73–83, 1990.
[11] Yuguang Yang and Yasunari Shidama. Trigonometric functions and existence of circle ratio. *Formalized Mathematics*, 7(**2**):255–263, 1998.

Received October 10, 2002